

1-channel mode (Dimmer)

Channel	Function	Values	Description
1	Dimmer	000 – 255	Master dimmer from 0 to 100%

2-channels mode (Dimmer 16 bit)

Channel	Function	Values	Description
1	Dimmer	000 – 255	Master dimmer from 0 to 100%
2	Dimmer fine	000 – 255	Dimmer fine

2-channels mode (02CH)

Channel	Function	Values	Description
1	Dimmer	000 – 255	Master dimmer from 0 to 100%
2	Strobe	000 – 031	Led ON
		032 – 063	Led OFF
		064 – 095	Strobe from slow to fast
		096 – 127	Open
		128 – 159	Pulse IN from slow to fast
		160 – 191	Open
		192 – 223	Random strobe from slow to fast
		224 – 255	Open

4-channels mode (Standard)

Channel	Function	Values	Description
1	Dimmer	000 – 255	Master dimmer from 0 to 100%
2	Dimmer fine	000 – 255	Dimmer fine
3	Strobe	000 – 031	Led ON
		032 – 063	Led OFF
		064 – 095	Strobe from slow to fast
		096 – 127	Open
		128 – 159	Pulse IN from slow to fast
		160 – 191	Open
		192 – 223	Random strobe from slow to fast
		224 – 255	Open
4	Dimmer mode	000 – 020	LED mode (display bypassed)
		021 – 040	Halogen mode (display bypassed)
		041 – 255	No function: display priority

5-channels mode (Extended)

Channel	Function	Values	Description
1	Dimmer	000 – 255	Master dimmer from 0 to 100%
2	Dimmer fine	000 – 255	Dimmer fine
3	Strobe	000 – 031	Led ON
		032 – 063	Led OFF
		064 – 095	Strobe from slow to fast
		096 – 127	Open
		128 – 159	Pulse IN from slow to fast
		160 – 191	Open
		192 – 223	Random strobe from slow to fast
		224 – 255	Open
4	Dimmer mode	000 – 020	LED mode (display bypassed)
		021 – 040	Halogen mode (display bypassed)
		041 – 255	No function: display priority
5	Control (wait 3 seconds after selecting the value)	000 – 100	No function
		101 – 105	LED refresh rate 900 Hz
		106 – 110	LED refresh rate 1000 Hz
		111 – 115	LED refresh rate 1100 Hz
		116 – 120	LED refresh rate 1200 Hz
		121 – 125	LED refresh rate 1300 Hz
		126 – 130	LED refresh rate 1400 Hz
		131 – 135	LED refresh rate 1500 Hz
		136 – 140	LED refresh rate 2500 Hz
		141 – 145	LED refresh rate 4000 Hz
		146 – 150	LED refresh rate 5000 Hz
		151 – 155	LED refresh rate 10000 Hz
		156 – 160	LED refresh rate 15000 Hz
		161 – 165	LED refresh rate 20000 Hz
		166 – 200	No function
		201 – 210	Dimmer curve LINEAR
		211 – 220	Dimmer curve SQUARE
		221 – 230	Dimmer curve INVERSE SQUARE
		231 – 240	Dimmer curve S-CURVE
		241 – 255	No function