

6-channels mode

Channel	Value	Instruction
1	000 - 255	Red
2	000 - 255	Green
3	000 - 255	Blue
4	000 - 255	White
5	000 - 255	Amber
6	000 - 255	UV

8-channels mode

Channel	Value	Instruction
1	000 - 255	Red
2	000 - 255	Green
3	000 - 255	Blue
4	000 - 255	White
5	000 - 255	Amber
6	000 - 255	UV
7	000 - 255	Dimmer
8	000 - 016	No functions
	017 - 255	Strobe from slow to fast

12-channels mode

Channel	Value	Instruction
1	000 - 255	Red
2	000 - 255	Green
3	000 - 255	Blue
4	000 - 255	White
5	000 - 255	Amber
6	000 - 255	UV
7	000 - 255	Dimmer
8	000 - 016	No functions
	017 - 255	Strobe from slow to fast
9	000 - 010	No functions
	001 - 030	R:100% G:100% B:0%
	031 - 050	R:100% - 0% G:100% B:0%
	051 - 070	R:0% G:100% B:0 - 100%
	071 - 090	R:0% G:100% - 0% B:100%
	091 - 110	R:0% - 100% G:0% B:100%
	111 - 130	R:100% G:0% B:100% - 0%
	131 - 150	R:100% G:0% - 100% B:0% - 100%
	151 - 170	R:100% - 0% G:100% - 0% B:100%
	171 - 200	R:100% G:100% B:100%
	201 - 205	White 1
	206 - 210	White 2
	211 - 215	White 3
	216 - 220	White 4
	221 - 225	White 5
	226 - 230	White 6
	231 - 235	White 7
	236 - 240	White 8
241 - 245	White 9	
246 - 250	White 10	
251 - 255	White 11	
10	000 - 010	No functions
	011 - 130	Macro fade
	131 - 255	Macro color change
11	000 - 209	Min speed CH10
	210 - 255	Speed from max to med CH10
12	000 - 016	No functions
	017 - 255	Sound mode